MTL4500 - MTL5500 RANGE COMMON SPECIFICATIONS

Please go to our website at www.mtl-inst.com for the latest information regarding safety approvals, certificates and entity parameters.

Connectors

Each unit is supplied with signal connectors, as applicable. When using crimp ferrules for the hazardous or non-hazardous (safe) signal connectors the metal tube length should be 12mm and the wire trim length 14mm.

Isolation

250V rms, tested at 1500V rms minimum, between safe- and hazardous-area terminals.

MTL4500: 50V between safe-area circuits and power supply MTL5500: 250V rms between safe-area circuits and power supply

Supply voltage

20 – 35V dc

Location of units

Safe area

ierminais

Accepts conductors of up to 2.5mm² stranded or single-core

Mounting

MTL4500

MTL4500 range of backplanes

MTL5500

T-section 35mm DIN rail (7.5 or 15mm) to EN 50022

Ambient temperature limits

-20 to +60°C (-6 to +140°F) operating

-40 to +80°C (-40 to +176°F) storage

Humidity

5 to 95% relative humidity

Weight

Approximate (except where indicated)

MTL4500 140g MTL5500 150g

ЕМС


To EN61326 and NE21*

HART® is a registered trademark of HART Communication Foundation


DIMENSIONS (MM)

MTL4500

Optional TH5000 tag holder for individual isolator identification. Accepts tag label 25 \times 12.5 ±0.5 mm, 0.2mm thick





16.0mm PITCH



MTL5500

Optional TH5000 tag holder for individual isolator identification. Accepts tag label 25 x 12.5 \pm 0.5mm, 0.2mm thick







Eaton Electric Limited,

Great Marlings, Butterfield, Luton Beds, LU2 8DL, UK. Tel. + 44 (0)1582 723633 Fax: + 44 (0)1582 422283 E-mail: mtlenquiry@eaton.com www.mtl-inst.com © 2016 Eaton All Rights Reserved Publication No.

EPSx5CS Rev4 010916

EUROPE (EMEA):

The given data is only intended as a product description and should not be regarded as a legal

+44 (0)1582 723633 mtlenquiry@eaton.com

+1 800 835 7075 mtl-us-info@eaton.com **ASIA-PACIFIC:** +65 6 645 9888 sales.mtlsing@eaton.com

^{*} For 20ms power interruption compliance, a suitable power supply must be used.